Cicada NAND PCB · parts list

In the order they go in. Tick each one as you solder it. Guide: messopedals.com/diy/onion-madder/pcb/cicada-nand/

	Qty	Value	Part	Spot it	On the board
☐	5	**1M**	resistor	brown, black, green	R9, R10, R11, R12, R13
☐	4	**10K**	resistor	brown, black, orange	R5, R6, R7, R8
☐	4	**1K**	resistor	brown, black, red	R1, R2, R3, R4
☐	1	**1N5817**	diode	band to K square pad	D1
☐	1	**1 nF**	ceramic cap	printed 102	C3
☐	1	**10 nF**	ceramic cap	printed 103	C1
☐	2	**100 nF**	ceramic cap	printed 104	C2, C9
☐	1	**1 µF**	ceramic cap	printed 105	C4
☐	4	**1 µF**	film cap	box, printed 105	C5, C6, C7, C8
☐	1	**CD4093**	chip, 14-pin	notch to square pad	U1
☐	1	**10 µF**	electrolytic	long leg to + square pad	C10
☐	1	**100 µF**	electrolytic	long leg to + square pad	C11
☐	4	**B1M**	pot, 16 mm	B = linear	RV1, RV2, RV3, RV4

Off the board

☐	1	DC jack and a 9V supply, center negative
☐	1	SPST toggle for power, between the DC jack's + lug and SW
☐	4	SPST toggles for the gates, if you want them. A touch plate or a photocell to GND works on the same pins
☐	1	3.5 mm mono jack for the output
☐		Hookup wire for the headers
☐		The Cicada NAND PCB